

ATA-5000 Series Preamplifier

Small signal amplification

Ultra low noise power supply

High gain



Applications

Used for infrared sensor detection

Used for detecting weak magnetic field sensor

Used for optical detection of phototransistors

Introduction

ATA-5000 series is a preamplifier for very small signal detection, powered by the ATA-P5000 preamplifier low-noise power supply (option). There are several models based on frequency band, gain, input resistance, etc.

Model	ATA-5210	ATA-5220	ATA-5310	ATA-5320	ATA-5410
Bandwidth (-3dB)	1kHz~5MHz	1kHz~5MHz	1kHz~10MHz	1kHz~10MHz	1kHz~20MHz
Input resistance	50Ω	50Ω	50Ω	50Ω	50Ω
Input conversion Noise voltage	Less than $0.7\text{nV}/\sqrt{\text{Hz}}$ (1kHz) $0.5\text{nV}/\sqrt{\text{Hz}}$ typ (1k~1MHz)	Less than $1.7\text{nV}/\sqrt{\text{Hz}}$ (1kHz) $1.5\text{nV}/\sqrt{\text{Hz}}$ typ (1k~1MHz)	Less than $0.7\text{nV}/\sqrt{\text{Hz}}$ (100kHz) $0.5\text{nV}/\sqrt{\text{Hz}}$ typ (10k~1MHz)	Less than $1.7\text{nV}/\sqrt{\text{Hz}}$ (100kHz) $1.5\text{nV}/\sqrt{\text{Hz}}$ typ (10k~1MHz)	Less than $1.2\text{nV}/\sqrt{\text{Hz}}$ (100kHz) $0.9\text{nV}/\sqrt{\text{Hz}}$ typ (10k~1MHz)
Input conversion Noise current	$7\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)	$13\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)	$7\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)	$13\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)	$7\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)
Maximum output voltage	2 Vp-p (50Ω)	2 Vp-p (50Ω)	2 Vp-p (50Ω)	2 Vp-p (50Ω)	2 Vp-p (50Ω)
Output resistance	50Ω	50Ω	50Ω	50Ω	50Ω
Voltage gain	46 dB	60 dB	46 dB	60 dB	46 dB
Size (W * H * D)	135*70*25mm				

Model	ATA-5420	ATA-5510	ATA-5520	ATA-5610	ATA-5620
Bandwidth (-3dB)	1kHz~20MHz	1kHz~50MHz	1kHz~50MHz	1kHz~100MHz	1kHz~100MHz
Input resistance	50Ω	50Ω	50Ω	50Ω	50Ω
Input conversion Noise voltage	Less than $1.9\text{nV}/\sqrt{\text{Hz}}$ (100kHz) $1.2\text{nV}/\sqrt{\text{Hz}}$ typ (10k~1MHz)	Less than $1.2\text{nV}/\sqrt{\text{Hz}}$ (100kHz) $0.9\text{nV}/\sqrt{\text{Hz}}$ typ (10k~1MHz)	Less than $1.9\text{nV}/\sqrt{\text{Hz}}$ (100kHz) $1.2\text{nV}/\sqrt{\text{Hz}}$ typ (10k~1MHz)	Less than 1.2 $\text{nV}/\sqrt{\text{Hz}}$ (100kHz) $0.9\text{nV}/\sqrt{\text{Hz}}$ typ (10k~1MHz)	Less than $1.9\text{nV}/\sqrt{\text{Hz}}$ (100kHz) $1.2\text{nV}/\sqrt{\text{Hz}}$ typ (10k~1MHz)
Input conversion Noise current	$13\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)	$7\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)	$13\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)	$7\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)	$13\text{pA}/\sqrt{\text{Hz}}$ typ (10kHz)
Maximum output voltage	2 Vp-p (50Ω)	2 Vp-p (50Ω)	2 Vp-p (50Ω)	2 Vp-p (50Ω)	2 Vp-p (50Ω)
Output resistance	50Ω	50Ω	50Ω	50Ω	50Ω
Voltage gain	60 dB	46 dB	60 dB	46 dB	60 dB
Size (W * H * D)	135*70*25mm				

ATA-P5000 preamplifier low noise power supply (option)
Specification
appendix

Name	ATA-P5000 Preamplifier Low Noise Power Supply
Supply Voltage	AC220V±10%, 50Hz
Output Voltage	DC15V
Maximum output current	200mA
Output noise voltage	< 50μVrms (10Hz to 20MHz)
Fuse	0.5A/250V
Operating temperature	0°C~45°C
Storage temperature	-20°C~50°C
Humidity	≤80%RH, 无冷凝

Modle	ATA-P5000
Description	Preamplifier Low Noise Power Supply
Accessories	1*Three-core power cord, 1*LEMO (0B FGG 2-pin) power cord, 1*Fuse, 1*Product Manual, 1*certificate, 1*Packing List, 1*Ex-factory test Report.
联系我们	029-88865020

Xi'an Aigtek Electronic Technology Co., Ltd.

Address: Zhicheng Business, No.17, Gaoxin 4th Road, Xi 'an Hi-tech Industrial Development Zone

Tel: (+86) 029-88865020

Email: aigtek01@gmail.com

Website: <http://www.aigtek.com>